

Commercial LED CLT97 15W T8 Plug & Play Mode Ballast List					NC	Incompatible	P	PF <0.85				
					N	Acoustic noise >20dB	T	THD >30%				
					S	Can't start-up	C	Compatible				
					F	Flicker after >2s start-up	/	Not tested				
					HT	High temperature	NA	Not applicable				
					No	Ballast No.	Ballast Brand	Part Number	Start Method	# of Lamps	BF	
Type	Value	DR G5S		DR G5S								
									120Vac	277Vac	120Vac	277Vac
1	1	Philips-Advance	ICN-2P32-N	IS	2	N	0.89	Parallel	C	C	C	C
2	3	Philips-Advance	IOP-2P32-N	IS	2	N	0.89	Parallel	C	C	C	C
3	4	Philips-Advance	IOP-2P32-LW-N	IS	2	L	0.77	Parallel	C	C	C	C
4	5	OSRAM SYLVANIA	QTP 2X32T8/UNV ISN-SC	IS	2	N	0.88	Parallel	C	C	C	C
5	6	OSRAM SYLVANIA	QHE 2X32T8/UNV ISN-SC	IS	2	N	0.88	Parallel	C	C	C	C
6	7	OSRAM SYLVANIA	QHE 2X32T8/UNV ISL-SC	IS	2	L	0.78	Parallel	C	C	C	C
7	8	General Electric	GE-232-MV-N	IS	2	N	0.88	Parallel	C	C	C	C
8	9	General Electric	GE232MAX-N/ULTRA	IS	2	N	0.88	Parallel	C	C	C	C
9	10	Universal Lighting Technologies	B232IUNVHP-N	IS	2	N	0.88	Parallel	N	N	C	C
10	11	Universal Lighting Technologies	B232IUNVEL-A	IS	2	L	0.77	Parallel	C	C	C	C
11	12	Universal Lighting Technologies	B233IUNVHE-A	IS	2	N	0.87	Parallel	C	C	C	C
12	13	ESPEN	VE232MVHIPE	IS	2	N	0.89	Parallel	C	C	C	C
13	14	ESPEN	VE232MVHIPHE	IS	2	H	1.19	Parallel	HT	HT	C	C
14	15	Philips-Advance	IOPA-3P32-LW-N	IS	3	L	0.76	Parallel	N	N	N	N
16	17	Philips-Advance		IS	4	N	0.87	Parallel	N	N	N	N
18	19	Philips-Advance	IOP-4P32-N	IS	4	N	0.87	Parallel	C	C	C	C
19	20	Philips-Advance	IOP-4P32-LW-N	IS	4	L	0.77	Parallel	C	C	C	C
20	21	Philips-Advance	ICN-4P32-N	IS	4	N	0.90	Parallel	C	C	C	C
21	22	General Electric	GE432MAX-H/ULTRA	IS	4	H	1.18	Parallel	C	C	C	C
24	25	OSRAM SYLVANIA	QHE 4X32T8/UNV ISL-SC	IS	4	L	0.78	Parallel	C	C	C	C
25	26	Philips-Advance	IOP-1P32-N	IS	1	N	0.89	n.a	NC	NC	NC	NC
26	27	Philips-Advance	IOP-2P32HL-SC	IS	2	H	1.18	Parallel	NC	NC	NC	NC
27	28	General Electric	GE-232-MAX-H/Ultra	IS	2	H	1.15	Parallel	NC	NC	NC	NC
28	29	HOWARD INDUSTRIES	EPH4/32IS/MV/SC/HE	IS	4	H	1.16	Parallel	NC	NC	NC	NC
29	30	HOWARD INDUSTRIES	EP3/32IS/MV/SC/HE	IS	3	N	0.87	Parallel	C	C	C	C
30	31	HOWARD INDUSTRIES	EPL4/32IS/MV/MC/HE	IS	4	L	0.77	Parallel	C	C	C	C
31	32	ProLume	EP232IS/L/MV/SL	IS	2	L	0.78	Parallel	C	C	C	C
32	33	ProLume	E432IS/120/R/SL	IS	4	N	0.87	Parallel	P,T	NA	P,T	NA
33	34	General Electric	GE432MAX-G-N	IS	4	N	0.88	Parallel	C	C	C	C
34	35	Universal Lighting Technologies	B432IUNVHE L-A	IS	4	L	0.77	Parallel	C	C	C	C
36	37	Philips-Advance	ICN-1P32-N	IS	1	N	0.91	n.a	NA	NA	NC	NC
37	38	Philips-Advance	IOPA-1P32-N	IS	1	N	0.88	n.a	NC	NC	NC	NC
38	39	General Electric	GE132MAX-G-N	IS	1	N	0.88	n.a	NA	NA	NC	NC
40	41	General Electric	GE132MAX-L/ULTRA	IS	1	L	0.78	n.a	NA	NA	NC	NC
41	42	General Electric	GE132MAXP-N/ULTRA	IS	1	N	0.88	n.a	NA	NA	C	C
43	44	OSRAM SYLVANIA	QHE 1X32T8/UNV ISL-SC	IS	1	L	0.78	n.a	NA	NA	C	C
44	46	ESPEN	VE232MVHIPE	IS	2	L	0.77	Parallel	C	C	C	C
45	48	Philips-Advance	REB-2P32-SC	IS	2	N	0.88	Parallel	F	NA	C	NA
46	49	General Electric	GE232MV-N-DIY	IS	2	N	0.88	Parallel	C	C	C	C
47	51	General Electric	GE232MAX-L/ULTRA	IS	2	L	0.78	Parallel	C	C	C	C
48	52	General Electric	GE232MAX347-N	IS	2	H	1.02	Parallel	NA	P,T(347V)	NA	C,(347V)
49	53	Halco	EP232IS/MV/HE	IS	2	N	0.88	Parallel	C	C	C	C
50	54	Universal Lighting Technologies	B232IUNVHEH-A	IS	2	H	1.18	Parallel	HT	HT	C	C
52	56	HOWARD INDUSTRIES	EPH2/32IS/MV/MC/HE	IS	2	H	1.18	Parallel	HT	HT	C	C
53	58	MAXLITE	SKEU322HEL/SC	IS	2	L	0.77	Parallel	C	C	C	C
55	61	Philips-Advance	IOPA-3P32-N	IS	3	N	0.86	Parallel	N	N	N	N
56	62	Philips-Advance	IOP-3P32-N	IS	3	N	0.87	Parallel	N	N	N	N
57	63	General Electric	GE332MV-N	IS	3	N	0.87	Parallel	C	C	C	C
58	64	General Electric	GE332MAX-N/ULTRA	IS	3	N	0.88	Parallel	C	C	C	C
59	65	General Electric	GE332MAX-L/ULTRA	IS	3	L	0.78	Parallel	C	C	C	C
60	66	General Electric	GE332MAX-G-N	IS	3	N	0.87	Parallel	C	C	C	C
61	67	General Electric	GE332MAXP-H/ULTRA	IS	3	H	1.18	Parallel	HT	HT	C	C
62	68	OSRAM SYLVANIA	QTP 3X32T8/UNV ISN-SC	IS	3	N	0.88	Parallel	C	C	C	C
63	69	OSRAM SYLVANIA	QHE 3X32T8/UNV ISN-SC	IS	4	N	0.88	Parallel	C	C	C	C
64	70	OSRAM SYLVANIA	QHE 3X32T8/UNV ISL-SC	IS	3	L	0.78	Parallel	C	C	C	C
65	71	Universal Lighting Technologies	B332IUNVHP-A	IS	3	N	0.88	Parallel	C	C	C	C
66	72	MAXLITE	SKEU324HE/SC	IS	4	N	0.88	Parallel	C	C	C	C
67	73	MAXLITE	SKEU323L/SC	IS	3	L	0.78	Parallel	C	C	C	C
68	74	Halco	EP332IS/MV/HE	IS	3	N	0.87	Parallel	C	C	C	C
69	76	Universal Lighting Technologies	B432IUNVHP-A	IS	4	N	0.88	Parallel	C	C	C	C
70	77	Halco	EP432IS/MV/HE	IS	4	N	0.88	Parallel	C	C	C	C
71	78	Halco	EP432IS/L/MV/HE	IS	4	L	0.78	Parallel	C	C	C	C
72	79	Philips-Advance	REB-4P32-SC	IS	4	N	0.81	Parallel	C	NA	C	NA
73	80	Philips-Advance	IOP-4P32-HL-SC	IS	4	H	1.18	Parallel	NC	NC	NC	NC
74	81	General Electric	GE432-120-RES	IS	4	N	0.83	Parallel	C	NA	C	NA
75	82	General Electric	GE432MV-N-42T	IS	4	N	0.93	Parallel	C	C	C	C
76	83	General Electric	GE432MAX-N/ULTRA	IS	4	N	0.88	Parallel	C	C	C	C
77	84	General Electric	GE432MAX347-N	IS	4	N	0.94	Parallel	NA	C,(347V)	NA	C,(347V)
78	85	MAXLITE	MLEU322HEL/SC	IS	2	N	0.83	Parallel	C	C	C	C
79	86	MAXLITE	MLEU323H/SC	IS	3	H	1.18	Parallel	C	C	C	C
80	87	TCP	E2P32ISUNVHE	IS	2	H	1.18	Parallel	HT	HT	C	C
81	88	TCP	E4P32ISUNVLE	IS	4	L	0.78	Parallel	C	F	C	C
82	89	Universal Lighting Technologies	B232120RES-A	IS	2	N	0.88	Parallel	T	NA	T	NA
83	91	General Electric	GE232MAXP90-V60	IS	2	H	1.18	Parallel	NC	NC	NC	NC
84	92	HOWARD INDUSTRIES	E2/32IS-120MC	IS	2	N	0.85	Parallel	T	NA	C	NA

Commercial LED CLT97 15W T8 Plug & Play Mode Ballast List					NC	Incompatible			P	PF <0.85		
					N	Acoustic noise >20dB			T	THD >30%		
					S	Can't start-up			C	Compatible		
					F	Flicker after >2s start-up			/	Not tested		
					HT	High temperature			NA	Not applicable		
85	93	HOWARD INDUSTRIES	EPL2/32IS/MV/MC/HE	IS	2	L	0.78	Parallel	C	T	C	C
86	94	PLUSRITE	BAF232IS/MV	IS	2	N	0.89	Parallel	C	C	C	C
87	95	General Electric	GE332MAXP90-V60	IS	3	H	1.18	Parallel	NC	NC	NC	NC
88	96	General Electric	GE432MAXP90-S60	IS	4	H	1.18	Parallel	NC	NC	NC	NC
89	97	EIKO	PM-2X32T8-UNV-IS-L	IS	2	L	0.77	Parallel	C	C	C	C
90	98	EIKO	PM-3X32T8-UNV-IS	IS	3	N	0.87	Parallel	C	C	C	C
91	99	EIKO	PM-3X32T8-UNV-IS-H	IS	3	H	1.18	Parallel	HT	HT	C	C
92	200	EIKO	PM-3X32T8-UNV-IS-L	IS	3	L	0.78	Parallel	C	C	C	C
93	201	HOWARD INDUSTRIES	EPL3/32IS/MV/SC/HE	IS	3	L	0.78	Parallel	C	C	C	C
94	202	PLUSRITE	BAF332IS/MV	IS	3	N	0.88	?	C	C	C	C
95	203	TCP	E3P32ISUNVE	IS	3	N	0.88	Parallel	C	C	C	C
96	204	TCP	E3P32ISUNVLE	IS	3	L	0.78	Parallel	C	F	C	C
97	205	TCP	E4P32ISUNVE	IS	4	N	0.88	Parallel	C	C	C	C
98	206	TCP	E4P32ISUNVHE	IS	4	N	1.18	Parallel	C	C	C	C
99	207	HOWARD INDUSTRIES	EP4/32IS/MV/MC/HE	IS	4	N	0.88	Parallel	C	C	C	C
100	210	EIKO	PM-4X32T8-UNV-IS	IS	4	N	0.88	Parallel	C	C	C	C
101	211	EIKO	PM-4X32T8-UNV-IS-L	IS	4	L	0.78	Parallel	C	C	C	C
102	212	Universal Lighting Technologies	B132IUNVHP-N	IS	1	N	0.88	n.a	NA	NA	F	C
103	213	SOLA	E-758-U-232-MC	IS	2	N	0.88	Parallel	C	C	NC	NC
104	214	HOWARD INDUSTRIES	EP2/32IS/MV/MC/HE	IS	2	N	0.89	Parallel	C	C	C	C
105	215	HOWARD INDUSTRIES	EP3 / 32IS / MV / MC / HE	IS	3	N	0.88	Parallel	C	C	C	C
106	216	WORK HORSE	WHSG3-UNV-T8-IS	IS	3	N	0.99	Parallel	C	C	C	C
107	217	WORK HORSE	WHSG4-UNV-T8-IS	IS	4	N	0.96	Parallel	C	C	C	C
108	218	KEYSTONE	KTEB-432RIS-1-TP-SL	IS	4	N	0.80	Parallel	C	NA	C	NA
109	219	MAXLITE	MLEU324HE/SC	IS	4	N	0.88	Parallel	C	C	C	C
110	220	SUNPARK	120-1/32IS HPF	IS	1	N	0.88	NA	NA	NA	C	NA
111	221	Superior Life	70201	IS	2	N	0.88	Parallel	C	F	C	C
112	222	SUNPARK	U-2/32IS HBF	IS	2	H	1.18	Parallel	C	C	C	C
113	223	SUNPARK	U-2/32ISE-LBF	IS	2	L	0.78	Parallel	C	C	C	C
114	224	SUNPARK	U-3/32ISE	IS	3	N	0.88	Parallel	C	C	C	C
115	225	SUNPARK	U-3/32ISE-HBF	IS	3	H	1.18	Parallel	HT	HT	C	C
116	226	SUNPARK	120-3/32IS MPF	IS	3	N	0.88	Parallel	C	NA	C	NA
117	227	SUNPARK	U-4/32IS HP,F	IS	4	N	0.88	Parallel	C	C	C	C
118	228	SUNPARK	U-4/32IS HBF	IS	4	H	1.18	Parallel	HT	HT	C	C
119	229	SUNPARK	U-4/32ISE-LBF	IS	4	L	0.77	Parallel	C	C	C	C
120	231	EIKO	PM-2X32T8-UNV-IS	IS	2	N	0.87	Parallel	C	C	C	C
121	232	KEYSTONE	KTEB-332-UV-IS-N-P	IS	3	N	0.87	Parallel	C	C	C	C
122	233	KEYSTONE	KTEB-432-UV-IS-N-P	IS	4	N	0.87	Parallel	C	C	C	C
123	234	General Electric	GE432MAX-H/ULTRA	IS	4	H	1.18	Parallel	C	C	C	C
124	235	Philips-Advance	ICN-3P32-N	IS	3	N	0.88	Parallel	N	N	N	N
125	236	Halco	EP232IS/L/MV/HE	IS	2	L	0.78	Parallel	C	C	C	C
126	237	Halco	EP232IS/H/MV/HE	IS	2	H	1.18	Parallel	C	C	C	C
127	238	Halco	EP332IS/L/MV/HE	IS	3	L	0.78	Parallel	C	C	C	C
128	239	Halco	EP432IS/120/MC	IS	4	n	0.88	Parallel	S	S	S	S
129	240	Philips-Advance	VEL-2P32-SC	IS	2	N	0.88	Parallel	NA	T	NA	C
130	241	Universal Lighting Technologies	B232IUNVHP-B	IS	2	N	0.88	Parallel	C	C	C	C
131	242	OSRAM SYLVANIA	QTP2x32T8/277 ISN-D	IS	2	L	0.78	Parallel	NA	C	NA	C
132	243	KEYSTONE	KTEB-232LBF-1-TP-PIC-EV	IS	2	N	0.88	Parallel	C	NA	C	NA
133	244	HATCH	HL232BIS/UV/HE/W	IS	2	N	0.9	Parallel	C	C	C	C
134	245	HATCH	HL432BIS/UV/HE/W	IS	4	N	0.9	Parallel	C	C	C	C
135	246	HOWARD INDUSTRIES	EPH3/32IS/MV/MC/HE	IS	3	N	0.91	Parallel	HT	HT	C	C
136	247	ARCATA	ACT 3P32ISUNVLE	IS	3	L	0.78	Parallel	C	C	C	C
137	248	LIGHTING PRODUCTS LIMITED	EB-332EBF-UV-TP-HE	IS	3	L	0.78	Parallel	C	C	C	C
138	249	General Electric	GE432MAX90-S60	IS	4	H	1.18	Parallel	C	C	C	C
139	250	KEYSTONE	KTEB-232-UV-IS-H-P	IS	2	H	1.18	Parallel	HT	HT	C	C
140	251	KEYSTONE	KTEB-332-UV-IS-H-P	IS	3	H	1.18	Parallel	HT	HT	C	C
141	252	KEYSTONE	KTEB-432-UV-IS-H-P	IS	4	H	1.18	Parallel	C	C	C	C
142	253	TOPAZ	B232IUNVHEH/A-TPZ	IS	2	H	1.18	Parallel	HT	HT	C	C
143	254	TOPAZ	B432IUNVHEH/A-TPZ	IS	4	H	1.18	Parallel	C	C	C	C
144	255	Universal Lighting Technologies	B232IUNV-C	IS	2	N	0.88	Parallel	C	C	C	C
145	256	DAMAR	EL232-120/277HF(1688B)	IS	2	N	?	Parallel	C	F	C	C
146	257	DAMAR	EL232HL-120/277HF(1688D)	IS	2	H	?	Parallel	C	C	C	C
147	258	DAMAR	EL332-120/277HF(3654C)	IS	3	N	?	Parallel	C	C	C	C
148	259	DAMAR	EL332HL-120/277HF(3654H)	IS	3	H	?	Parallel	C	C	C	C
149	260	DAMAR	EL432-120/277HF(3093B)	IS	4	N	?	Parallel	C	C	C	C
150	261	DAMAR	EL432HL-120/277HF(3093C)	IS	4	H	?	Parallel	C	C	C	C
151	262	Philips-Advance	IOPA-2P32-HL-N	IS	2	H	1.18	Parallel	N	N	N	N
152	263	Plusrite	BAF232IS/MV/L	IS	2	L	0.78	Parallel	C	C	C	C
153	264	Plusrite	BAF332IS/MV/L	IS	3	L	0.78	Parallel	C	C	C	C
154	265	Plusrite	BAF432IS/MV	IS	4	N	0.88	Parallel	C	C	C	C
155	266	Plusrite	BAF432IS/MV/L	IS	4	L	0.78	Parallel	C	C	C	C
156	267	OSRAM SYLVANIA	QT2X32/120 IS-SC	IS	2	N	0.9	Parallel	P,T	NA	C	NA
157	268	Watran	DB-232N-MV-TP-HE	IS	2	N	0.87	Parallel	C	C	C	C
158	269	Watran	DB-332N-MV-TP-HE	IS	3	N	0.87	Parallel	C	C	C	C
159	270	Watran	DB-432N-MV-TP-HE	IS	4	N	0.87	Parallel	C	C	C	C

Commercial LED CLT97 15W T8 Plug & Play Mode Ballast List					NC	Incompatible	P	PF <0.85				
					N	Acoustic noise >20dB	T	THD >30%				
					S	Can't start-up	C	Compatible				
					F	Flicker after >2s start-up	/	Not tested				
					HT	High temperature	NA	Not applicable				
160	271	Watran	DB-432L-MV-TP-HE	IS	4	L	0.77	Parallel	C	C	C	C
161	272	Watran	DB-232N-MV-TP-HE (SC)	IS	2	N	0.87	Parallel	C	C	C	C
162	273	ACT	ACT 2P32ISUNVE	IS	2	N	0.89	Parallel	C	C	C	C
163	274	ANTRON ELECTRONICS	A32T8MICLO	IS	2	L	0.78	Parallel	C	C	C	C
164	277	EIKO	PM-2x32T8-UNV-IS-H	IS	2	H	1.18	Parallel	HT	HT	C	C
165	279	OSRAM SYLVANIA	QHE 3x32T8/UNV ISH HT-SC	IS	3	H	1.18	Parallel	HT	HT	C	C
166	280	Philips-Advance	VEL-2P32-RH-TP	IS	2	N		Parallel	NA	P,T	NA	C
167	281	OSRAM SYLVANIA	QHE 4x32T8/UNV ISH HT-1	IS	4	H	1.18	Parallel	C	C	C	C
168	282	Philips-Advance	IOP-3P32HL-90C-SC	IS	3	H	1.22	Parallel	NC	NC	NC	NC
169	283	TCP	TCP3P32ISUNVH	IS	3	H	1.18	Parallel	HT	HT	C	C
170	284	Philips-Advance	IOP-4P32-SC	IS	4	N	0.87	Parallel	S	S	S	S
171	286	Philips-Advance	IOPA-4P32-SC	IS	4	N	0.92	Parallel	C	C	C	C
172	287	Universal Lighting Technologies	B432IUNVHE-A	IS	4	N	0.87	Parallel	C	C	C	C
173	288	Universal Lighting Technologies	B432IUNVHEH-E	IS	4	H	1.15	Parallel	C	C	C	C
174	289	General Electric	GE232MAX-G-L	IS	2	L	0.77	Parallel	C	C	C	C
175	290	OSRAM SYLVANIA	QHE 2X32T8/UNV ISH HT-SC	IS	2	H		Parallel	HT	HT	C	C
176	291	OSRAM SYLVANIA	QHE 4x32T8/UNV ISH-SC	IS	4	H		Parallel	NC	NC	NC	NC
177	292	General Electric	GE332MAXP-L/ULTRA	IS	3	L	0.77	Parallel	C	C	C	C
178	293	Universal Lighting Technologies	B232I277RH-A	IS	4	H	1.09	Parallel	NA	T	NA	C
179	295	Pacific Fluorescent	EB-232IS-120-RES	IS	2	N		Parallel	C	NA	C	NA
180	296	OSRAM SYLVANIA	QT 2x32/347 ISH-SC	IS	2	H	1.20	Parallel	NA	NA	NA	C,(347V)
181	297	OSRAM SYLVANIA	QHE 1X32T8/UNV ISH-SC	IS	1	H	1.20	NA	NA	NA	C	P,T
182	298	Philips-Advance	ICN-132-MC	IS	1	N	0.88	NA	NA	NA	C	C
183	299	Philips-Advance	ICN-2P16-TLED-N	IS	2	N		Parallel	C	C	C	C
184	1001	Philips-Advance	ICN-4P16-TLED-N	IS	4	N		Parallel	C	C	C	C
185	1002	ESPEL	VE2P32MVHIPE	IS	2	N	0.89	Parallel	C	C	C	C
186	1003	General Electric	GE232MAX-G-N	IS	2	N	0.88	Parallel	C	C	C	C
187	1004	Universal Lighting Technologies	B332IHRVHB-E	IS	3	H	/	Parallel	S	S	S	S
188	1005	General Electric	GE-232-MAX-H-42T	IS	2	H	/	Parallel	HT	HT	HT	HT
189	1006	General Electric	GE432MAX-H-42T	IS	4	H	/	Parallel	C	T	C	T
190	1007	Cooper Lighting	CL-432ISUNV-R1-B	IS	4	H	1.18	Parallel	C	C	C	C
191	1008	TCP	E3P32ISUNVHE	IS	3	H	/	Parallel	C	C	C	C
192	1009	General Electric	332MAX-H-84TS	IS	3	H	/	Parallel	C	C	C	C
193	1010	General Electric	332MAX-H-42T	IS	3	H	/	Parallel	C	C	C	C
194	1011	General Electric	GE432MAX-G-H	IS	4	H	1.18	Parallel	C	C	C	C
195	1012	Philips-Advance	ICN-3P32-SC	IS	3	N	0.89	Parallel	C	C	C	C
196	1013	Philips-Advance	VEL-3P32-SC	IS	3	N	0.88	Parallel	C	C	C	C
197	1014	Philips-Advance	REL-2P32-RH-TP	IS	2	H	/	Parallel	C	C	C	C
198	1015	Philips-Advance	GOPA-2P32-N	IS	2	N	/	Parallel	C	C	C	C
199	1016	Philips-Advance	IOPA-4P32-HL	IS	4	H	1.18	Parallel	C	C	C	C
200	1018	SYLVANIA	QT 3x32/277 IS	IS	3			Parallel	NA	C	NA	C
201	102	Philips-Advance	IOP-3PSP32-SC	PS	3	N	0.88	Parallel	C	C	C	C
202	104	Philips-Advance	IOP-4PSP32-SC	PS	4	N	0.89	Parallel	C	C	C	C
203	105	Philips-Advance	IOP-4PSP32-LW-SC	PS	4	L	0.69	Parallel	C	C	C	C
204	112	Universal Lighting Technologies	B432PUNVHE-A	PS	4	N	0.87	Parallel	C	C	C	C
205	113	General Electric	GE232-MVPS-N	PS	2	N	0.88	Parallel	C	C	C	C
206	116	OSRAM SYLVANIA	QHE 2X32T8/UNV PSN-MC	PRS	2	N	0.88	Parallel	C	C	C	C
207	120	General Electric	GE-332-MVPS-N	PS	3	N	0.88	Parallel	C	C	C	C
208	121	OSRAM SYLVANIA	QHE 3X32T8/UNV PSN-SC	PRS	3	N	0.88	Parallel	C	C	C	C
209	126	OSRAM SYLVANIA	QHE 4X32T8/UNV PSN-SC	PRS	4	N	0.88	Parallel	C	C	C	C
210	128	Watran	DBG32N-MV-TP-PS-HL	PS	3	H			S	S	S	S
211	129	General Electric	GE-232-MV-PS-N	PS	2	N	0.88	Parallel	C	C	C	C
212	140	SUNPARK	SL15T	PS	2	N	0.88	Series	S	NA	S	NA