



IZT-4P16-TLED-SC @ 120V				
Brand Name	Mark 7 0-10V			
Driver Type	<b>Electronic Dimming</b>			
Lamp Connection	Parallel			
Input Voltage	120V			
Input Frequency	50/60 Hz			
Status	Active			

Compatible Lamp Information						Driver Specifications @120V							
T8 LED Lamp Brand	T8 LED Lamp Description	T8 LED Lamp Product No.	T8 LED Lamp Model No.	T8 LED Lamp Ordering Code	Bare Lamp Watts (W)	Nom. Initial Lumens	Min. Start Temp (°F/°C)	Num. of Lamps	Input Current (A)	Input Power (W) (Min/Max)	I HI 19/2	Power Factor	
Philips	LED InstantFit T8 - 4'	468306 468314	9290011585C 9290011586C	14T8/48-3000 IF 10/1 HO 14T8/48-3500 IF 10/1 HO	14 2000 2100	2000 2000	-13/-25	4	0.59	5 / 71	10	0.99	
Fillips	High Output	468322 468330	9290011587C 9290011588C	14T8/48-4000 IF 10/1 HO 14T8/48-5000 IF 10/1 HO		2100 2100		3	0.46	5 / 55	10	0.99	
Philips	LED InstantFit T8 - 4'	468892 463133	9290013044 9290012267	16.5T8 LED/48-3000 IF 10/1 HO 16.5T8 LED/48-3500 IF 10/1 HO	16 F		2300 2400	-13/-25	4	0.71	6 / 84	10	0.99
FIIIIPS	High Output	463141 463158	9290012268 9290012269	16.5T8 LED/48-4000 IF 10/1 HO 16.5T8 LED/48-5000 IF 10/1 HO	10.5	2500 2500	-13/-23	3	0.55	5 / 66	10	0.99	













Revised: 01/11/17

Data is based on tests performed by Philips Lighting NA in a controlled environment and is representative of relative performance. Actual performance can vary depending on operating conditions.

Specifications are subject to change without notice. All specifications are nominal unless otherwise noted.



IZT-4P16-TLED-SC @ 120V					
Brand Name	Mark 7 0-10V				
Driver Type	Electronic Dimming				
Lamp Connection	Parallel				
Input Voltage	120V				
Input Frequency	50/60 Hz				
Status	Active				

### Notes:

### Section I - Physical Characteristics

- 1.1 Driver shall be physically interchangeable with standard electromagnetic or standard electronic ballasts, where applicable.
- 1.2 Driver shall be provided with integral leads color coded per ANSI C82.11.

#### Section II - Performance Requirements

- 2.1 Driver shall energize compatible LED lamps within 1 second after mains power is applied.
- 2.2 Driver shall provide Independent Lamp Operation (ILO) allowing remaining lamp(s) to maintain full light output when one or more lamps fail.
- 2.3 Driver shall contain auto restart circuitry in order to restart lamps without resetting power.
- 2.4 Driver shall operate from a 50Hz or 60 Hz AC input source of 120V through 277V with sustained variations of +/- 10% (voltage and frequency).
- 2.5 Driver shall be high frequency electronic type and operate lamps at frequencies above 42 kHz to avoid interference with infrared devices and eliminate visible flicker.
- 2.6 Driver shall have a Power Factor of 0.94 or above when operating the maximum rated number of compatible lamps, and 0.88 or above when operating the minimum rated number of compatible lamps.
- 2.7 Driver input current shall Total Harmonic Distortion (THD) of 10% or less when operating the maximum rated number of compatible lamps and 15% or less when operating the minimum rated number of compatible lamps.
- 2.8 Driver shall have a Class A sound rating.
- 2.9 Driver shall have a minimum starting temperature of -13°F / -25°C
- 2.10 Driver shall tolerate sustained open circuit and short circuit output conditions.
- 2.11 Driver shall control lamp light output from 100% 5% relative light output for T8 TLED.
- 2.12 Driver shall be suitable of operation in up to a 45°C ambient temperature.

#### Section III - Regulatory Requirements

- 3.1 Driver shall not contain any Polychlorinated Biphenyl (PCB).
- 3.2 Driver shall be Underwriters Laboratories (UL) Recognized, Class P, and suitable for Damp and Dry conditions; and CSA Certified where applicable.
- 3.3 Driver shall comply with ANSI C62.41 Category A Transient protection.
- 3.4 Driver shall comply with the requirements of the Federal Communication Commission (FCC) rules and regulations, Title 47, CFR part 15, Non-Consumer (Class A) for EMI/RFI (conducted and radiated).
- 3.5 Driver shall comply with NEMA 410 for in-rush current limits.


### Section IV - Other


- 4.1 Driver shall be manufactured in a factory certified to ISO 9001 Quality System Standards.
- 4.2 Driver shall carry a five year warranty from date of manufacture against defects in material and workmanship when operating in a 45°C ambient envi



IZT-4P16-TLED-SC @ 277V						
Brand Name	Mark 7 0-10V					
Driver Type	<b>Electronic Dimming</b>					
Lamp Connection	Parallel					
Input Voltage	277V					
Input Frequency	50/60 Hz					
Status	Active					

Compatible Lamp Information							Driver Specifications @277V						
T8 LED Lamp Brand	T8 LED Lamp Description	T8 LED Lamp Product No.	T8 LED Lamp Model No.	T8 LED Lamp Ordering Code	Bare Lamp Watts (W)	Nom. Initial Lumens	Min. Start Temp (°F/°C)	Num. of Lamps	Input Current (A)	Input Power (W) (Min/Max)	Max THD%	Power Factor	
Philips	LED InstantFit T8 - 4'	468306 468314	9290011585C 9290011586C	14T8/48-3000 IF 10/1 HO 14T8/48-3500 IF 10/1 HO	14	2000 2000	-13/-25	4	0.25	5 / 69	10	0.97	
гишра	High Output	468322 468330	9290011587C 9290011588C	14T8/48-4000 IF 10/1 HO 14T8/48-5000 IF 10/1 HO		2100 2100		3	0.20	5 / 54	10	0.96	
Philips	LED InstantFit T8 - 4'	468892 463133	9290013044 9290012267	16.5T8 LED/48-3000 IF 10/1 HO 16.5T8 LED/48-3500 IF 10/1 HO	16.5	16.5	2300 2400	-13/-25	4	0.30	6 / 82	10	0.98
Fillips	3 1	463141 463158	9290012268 9290012269	16.5T8 LED/48-4000 IF 10/1 HO 16.5T8 LED/48-5000 IF 10/1 HO		2500 2500	-13/ <b>-</b> 23	3	0.24	5 / 65	10	0.97	













Revised: 01/11/17

Data is based on tests performed by Philips Lighting NA in a controlled environment and is representative of relative performance. Actual performance can vary depending on operating conditions. Specifications are subject to change without notice. All specifications are nominal unless otherwise noted.



IZT-4P16-TLED-SC @ 277V					
Brand Name	Mark 7 0-10V				
Driver Type	Electronic Dimming				
Lamp Connection	Parallel				
Input Voltage	277V				
Input Frequency	50/60 Hz				
Status	Active				

### Notes:

### Section I - Physical Characteristics

- 1.1 Driver shall be physically interchangeable with standard electromagnetic or standard electronic ballasts, where applicable.
- 1.2 Driver shall be provided with integral leads color coded per ANSI C82.11.

### Section II - Performance Requirements

- 2.1 Driver shall energize compatible LED lamps within 1 second after mains power is applied.
- 2.2 Driver shall provide Independent Lamp Operation (ILO) allowing remaining lamp(s) to maintain full light output when one or more lamps fail.
- 2.3 Driver shall contain auto restart circuitry in order to restart lamps without resetting power.
- 2.4 Driver shall operate from a 50Hz or 60 Hz AC input source of 120V through 277V with sustained variations of +/- 10% (voltage and frequency).
- 2.5 Driver shall be high frequency electronic type and operate lamps at frequencies above 42 kHz to avoid interference with infrared devices and eliminate visible flicker.
- 2.6 Driver shall have a Power Factor of 0.94 or above when operating the maximum rated number of compatible lamps, and 0.88 or above when operating the minimum rated number of compatible lamps.
- 2.7 Driver input current shall Total Harmonic Distortion (THD) of 10% or less when operating the maximum rated number of compatible lamps and 15% or less when operating the minimum rated number of compatible lamps.
- 2.8 Driver shall have a Class A sound rating.
- 2.9 Driver shall have a minimum starting temperature of -13°F / -25°C.
- 2.10 Driver shall tolerate sustained open circuit and short circuit output conditions.
- 2.11 Driver shall control lamp light output from 100% 5% relative light output for T8 TLED.
- 2.12 Driver shall be suitable of operation in up to a 45°C ambient temperature.

#### Section III - Regulatory Requirements

- 3.1 Driver shall not contain any Polychlorinated Biphenyl (PCB).
- 3.2 Driver shall be Underwriters Laboratories (UL) Recognized, Class P, and suitable for Damp and Dry conditions; and CSA Certified where applicable.
- 3.3 Driver shall comply with ANSI C62.41 Category A Transient protection.
- 3.4 Driver shall comply with the requirements of the Federal Communication Commission (FCC) rules and regulations, Title 47, CFR part 15, Non-Consumer (Class A) for EMI/RFI (conducted and radiated).
- 3.5 Driver shall comply with NEMA 410 for in-rush current limits.

### Section IV - Other

- 4.1 Driver shall be manufactured in a factory certified to ISO 9001 Quality System Standards.
- 4.2 Driver shall carry a five year warranty from date of manufacture against defects in material and workmanship when operating in a 45°C ambient environment.