

COMMERCIAL LED - T8 DUAL MODE BALLAST COMPATIBILITY

Brand	Model Number	Ballast Type	1 Lamp	2 Lamps	3 Lamps	4 Lamps
GE	GE332MAX-G-N-DIYB	IS	120V or 277V	120V or 277V	120V or 277V	
GE	GE259MAX-G-N-DIYB	IS	120V or 277V	120V or 277V	NO	
GE	GE232MAX-N/ULTRA	IS	120V or 277V	120V or 277V	NO	
QUICKTRONIC	QTP2x59 T8/UNV ISL-SC	IS	120V or 277V	120V or 277V	NO	
QUICKTRONIC	QHE2x59 T8/UNV ISL-SC	IS	120V ONLY	120V ONLY	NO	
ARCATA	ACT2P321SUNVE		120V or 277V	120V or 277V	NO	
ARCATA	ACT3P321SUNVE		120V or 277V	120V or 277V	120V or 277V	
ARCATA	ACT4P321SUNVE		120V or 277V	120V or 277V	120V or 277V	
GE	GE240RES120-DIYB	RS	120V or 277V	120V or 277V	NO	
GE	GE240RES120-B	RS	120V or 277V	120V or 277V	NO	
GE	GE240RES120-4PK	RS	120V or 277V	120V or 277V	NO	
ESPEN	VE2P32MVHIPL	IS		120V or 277V		
ESPEN	VE2P32MVHIPHE	IS		120V or 277V		
ESPEN	VE2P32MVHPPE	PS		120V or 277V		
ESPEN	VE2P32MVHIPE	IS		120V or 277V		
ESPEN	VE3P32MVHIPHE	IS		120V or 277V		
ESPEN	VE3P32MVHPPE	PS			120V or 277V	
ESPEN	VE3P32MVHIPE	IS			120V or 277V	
ESPEN	VE4P32MVHIPE	IS				120V or 277V
ESPEN	VE4P32MVHPPE	PS				120V or 277V
ESPEN	VE4P32MVHIPHE	IS				120V or 277V
ESPEN	VE4P32MVHIPL	IS	120V or 277V	120V or 277V	120V or 277V	120V or 277V
ESPEN	VE3P32MVHIPL	IS	120V	120V or 277V	120V or 277V	
EIKO	PM-2X32T8-UNV-IS	IS		120V or 277V		
EIKO	PM-3X32T8-UNV-IS	IS			277V	
EIKO	PM-3X32T8-UNV-IS-H	IS			277V	
EIKO	PM-4X32T8-UNV-IS	IS				277V
GE	GE132MAXP-L/ULTRA	IS	120V or 277V			
GE	GE232-120RES-B	IS	120V	120V		
GE	GE432MAXG-N-DIYL	IS				120V or 277V
GE	GE432-120RES-B	IS				120V
GE	GE332MAX-G-N-DIYB	IS			120V	
GE	GE232MAX-N/ULTRA	IS	120V	120V		
GE	GE132MAX-H/ULTRA	IS	120V or 277V			
GE	GE232MAX-L/ULTRA	IS		277V		
GE	GE232-MV-N	IS		120V or 277V		
GE	GE232-MVPS-N	RS		120V or 277V		
GE	GE232-MV-PS-H	RS		120V or 277V		
GE	GE232-MVPS-L	RS		120V or 277V		
GE	GE332MVPS-XL	RS			120V or 277V	
GE	GE432-120-RES	IS				120V
GE	GE232MAX-G-N	IS		120V or 277V		
GE	GE332MAX-G-N	IS			120V or 277V	
GE	GE 432MAXP-L/ULTRA	IS				120V or 277V
GE	GE 432MAXP-H/ULTRA	IS				120V or 277V
GE	GE 332MAXP-N/ULTRA	IS			120V or 277V	

COMMERCIAL LED - T8 DUAL MODE BALLAST COMPATIBILITY

Brand	Model Number	Ballast Type	1 Lamp	2 Lamps	3 Lamps	4 Lamps
GE	GE 332MAXP-L/ULTRA	IS			120V or 277V	
HALCO	E432IS/120R/MC	IS				120V or 277V
HALCO	EP232IS/MV/HE	IS		120V or 277V		
HALCO	EP332IS/MV/HE	IS			120V or 277V	
HALCO	EP332IS/L/MV/HE	IS			120V or 277V	
HALCO	EP432IS/L/MV/HE	IS				120V or 277V
DAMAR	1688B	IS		120V or 277V		
DAMAR	1688D	IS		120V or 277V		
DAMAR	3654C	IS			120V or 277V	
HOWARD INDUSTRIES	EP2/32IS/MV/MC/HE	IS				120V or 277V
HOWARD INDUSTRIES	EP4/32IS/MV/MC/HE	IS				120V or 277V
HOWARD INDUSTRIES	EPH4/32IS/MV/SC/HE	IS				120V or 277V
HOWARD INDUSTRIES	EPL2/32ISMV/MC/HE	IS		120V or 277V		
HOWARD INDUSTRIES	EPL3/32ISMV/SC/HE	IS			120V or 277V	
HOWARD INDUSTRIES	EPL4/32ISMV/MC/HE	IS				120V or 277V
OSRAM SLYVANIA	QHE2X32T8/UNV ISN-SC	IS	120V or 277V	120V or 277V		
OSRAM SLYVANIA	QHE4X32T8/UNV ISN-SC	RS	120V or 277V	120V or 277V	120V or 277V	120V or 277V
OSRAM SLYVANIA	QHE2X32T8/UNV-PSN-MC	RS		120V or 277V		
OSRAM SLYVANIA	QHE 4*32T8/UNV/ PSX-SC	RS				120V or 277V
PHILIPS-ADVANCE	REB-2P32-N	IS	120V	120V		
PHILIPS-ADVANCE	ICN-2P32-N	IS	120V or 277V	120V or 277V		
PHILIPS-ADVANCE	REB-4P32-SC	IS	120V	120V	120V	120V
PHILIPS-ADVANCE	IOPA-3P32-N	IS	120V or 277V	120V or 277V	120V or 277V	
PHILIPS-ADVANCE	IOP-4PSP32-LW-SC	PS	120V or 277V	120V or 277V	120V or 277V	120V or 277V
PHILIPS-ADVANCE	ICN-1P32-N	IS	120V or 277V			
PHILIPS-ADVANCE	IOPA-1P32-N	IS	120V or 277V			
PHILIPS-ADVANCE	ICN-2P32-N	IS		120V or 277V		
PHILIPS-ADVANCE	IOP-2P32-N	IS		120V or 277V		
PHILIPS-ADVANCE	IOP-4PSP32-SC	PS				120V or 277V
PHILIPS-ADVANCE	IOPA-3P32-LW-N	IS			120V or 277V	
PHILIPS-ADVANCE	IOPA-4P32-N	IS				120V or 277V
TCP	E4P32ISUNVE	IS				120V or 277V
TCP	E3P32ISUNVE	IS			120V or 277V	
TCP	E4P32ISUNVHE	IS				120V or 277V
KEYSTONE	KTEB-332-UV-IS-N-P	IS				120V or 277V
ULT	B232/UNVHP-N	IS	120V or 277V	120V or 277V		
ULT	B232PUNVHE-B	PS	120V or 277V	120V or 277V		
ULT	B332/UNVHP-A	IS	120V or 277V	120V or 277V	120V or 277V	
ULT	B232/UNVEL-N	RS	120V or 277V	120V or 277V		
ULT	B432PUMVHE-A	RS	120V or 277V	120V or 277V	120V or 277V	120V or 277V

NOTE:

1. The ballasts model list on the chart have been tested and approved by the manufacturer.
2. This list is to be used as a general guideline. The LED tube may not work if the ballast is over 5 years old or has a weak starting voltage.
3. Please strictly follow the wiring diagram shown on the ballasts.
4. Please check if the contact points of the old fixture work normal.
5. Please use caution and test lamps in fixtures for an extended period of time to ensure proper operation.
6. Do NOT proceed with a mass installation until proper operation of the LED tube is verified.
7. For safety, please turn off power while installing tubes.